



CNT-Scan MiniModule

- ▶ Very compact CAN measurement module
- ▶ 4 electrically isolated inputs for
 - ▶ frequency measurement
 - ▶ cycle/pulse duration
 - ▶ duty cycle/PWM
 - ▶ event counter and speed
 - ▶ time offset measurement
- ▶ User selectable On-/Off-Trigger thresholds for each individual channel, switchable AC coupling
- ▶ Sensor excitation
- ▶ Operating temperature:
-40 °C to +125 °C
- ▶ Robust aluminium housing: IP67
- ▶ Excellent price-performance ratio with 8 logical channels



CNT-Scan MiniModule

The **CNT-Scan MiniModule** is a high-precision measurement module for frequencies up to 300 kHz, for measurement of duty cycles/PWM signals, cycle/pulse duration measurement as well as event counting. Speed measurement (RPM) is calculated directly in the module and displayed as value on the CAN bus. Additionally, the time/event offset between adjacent channels can be measured.

The inputs are completely electrically isolated and connected sensors can be powered directly from the module. Each measurement mode requires only one signal input, however, one signal input can simultaneously collect two measurement parameters from the same physical signal – thereby allowing for up to 8 logical channels.

User selectable per-channel triggering for On and Off signal levels is supported. The **On-/Off-Trigger thresholds** are individually adjustable for each channel. Switchable AC coupling allows for suppression of undesired DC offset of the input signal.

Users need not be concerned with which measuring procedures should be used. High frequencies as well as low frequencies are automatically captured with **constant high accuracy**. This applies also to short and long periods and pulses.

Depending on the selected measurement mode many useful configuration options are available:

- ▷ Selectable Edge Detection: for measurements of rising or falling edges, and whether or not an "active high" or "active low" signal is measured, allowing for measurement of unusual signal forms.
- ▷ Configurable Timeout Value: e.g. for setting the minimum measurable frequency.
- ▷ Event Counting: additional counting mode (overflow/saturation), resetting properties and overflow/saturation values are configurable.
- ▷ Direct Speed Measurement (RPM): the number of counting pulses and missing teeth are configurable.
- ▷ Channel-to-Channel Time Offset: measures the time difference of events between two channels. A selectable input edge marks the beginning of the measurement; a selectable edge of an adjacent input marks the end of the measurement.

Accessories

Cables for CAN and power supply, CAN adapter cable, signal cables for sensor connection, CAN bus termination and mounting angles. For further details please consult the data sheet „**Accessories for CSM MiniModules**“.

CSM GmbH

Raiffeisenstr. 34, 70794 Filderstadt, Germany
Phone: +49 711 77964-20 Fax: +49 711 77964-40

E-Mail: info@csm-products.com

www.csm-products.com

Specifications CNT-Scan MiniModule

Technical data	CNT-Scan MiniModule
Inputs / Logical channels Input signal level On-/Off-Trigger thresholds Operating modes and measurement ranges	4 / 8 ± 60 V DC ± 5 V, in 10 mV steps or ± 50 V, in 100 mV steps each channel separately adjustable, AC coupling switchable frequency measurement: 0.1 Hz to 300 kHz cycle/pulse duration: 1 μ s to 100 s duty cycle/PWM: 0 % to 100 % event counter: 0 to 65535 (16 bit) speed: 0.01 rpm to 60000 rpm time offset measurement: 1 μ s to 100 s approx. 60 ns 1, 2, 5, 10, 20, 50, 100, 200, 500, 1000 Hz ± 100 V permanent, additional ESD protection 5 V, 8 V, 10 V, 12 V, 15 V DC average max. 30 mA each channel ¹⁾ , switchable by software
Internal resolution Measurement data rate per channel Input protection Sensor excitation	0,01 % of reading + 1LSB max. 100 ppm over complete temperature range
Accuracy at 25 °C Temperature drift	0,01 % of reading + 1LSB max. 100 ppm over complete temperature range
Galvanical isolation Channel / Channel CAN / Channel CAN / Power supply	500 V DC 500 V DC 500 V DC
CAN interface Configuration	CAN2.0B (active), High-Speed CAN (ISO 11898) 125 kBit/s to max. 1 MBit/s, data transfer is free running via CAN bus with CSM Config Tool or CSM INCA AddOn settings and configuration data are stored within device alternative: Configuration and data transfer via CANopen protocol ²⁾
LED Power / Status	LED: Power (green) / Status (red)
Power supply Power consumption (without sensor excitation)	approx. 5 V to 60 V DC typ. 1.4 W
Housing Dimensions (W x H x D) Weight	Aluminium – gold anodized approx. 93 x 30 x 46 mm (approx. 3.66 x 1.18 x 1.81 inch) Slide Case: approx. 120 x 37 x 50 mm (approx. 4.72 x 1.46 x 1.97 inch) approx. 230 g (approx. 8.11 oz) Slide Case: approx. 300 g (approx. 10.58 oz)
Operating temperature Storage temperature Relative humidity Protection	-40 °C to +125 °C (-40 °F to +257 °F) -55 °C to +150 °C (-67 °F to +302 °F) 5 % to 95 % IP67
Connector CAN / Voltage Signal inputs	LEMO 0B 5-pole³⁾ LEMO 0B 6-pole³⁾
Conformity	CE

1) 120mA in total, is distributed variable on the 4 channels

2) CANopen: see separate data sheet

3) Optional available in other variants

Shipping content CAN bus MiniModule, CSM ConfigTool, documentation, calibration certificate

We recommend a calibration interval of 1 year. For further technical information and references please ask our technical sales and distribution.

Part numbers

ART0200927	CNTMM 4 (Slide Case)
ART0200990	CNTMM 4