

AD pro CAN MM Series

Type MC10 | MC2



Product description

AD pro measurement modules feature 4 or 8 differential, galvanically isolated voltage inputs. They are also equipped with a very precise, bipolar sensor excitation, which is adjustable per channel.

AD pro measurement modules cover an extremely wide range of applications. They can be used for voltage measurement, high-precision current measurement (via shunts), measurement of very low voltages (such as strain gauge based sensors measuring at mV levels), and the acquisition of higher frequency signals with measurement data rates up to 10 kHz.

CAN

Key features

- ▶ Measurement inputs adjustable per channel from ± 10 mV to ± 60 V
- ▶ Measurement data rate per channel up to 10 kHz (AD4 pro MC10)
- ▶ Sensor linearization with interpolation points
- ▶ TEDS functionality according to IEEE 1451.4 (template 30 + template 40)
- ▶ Status LED per channel

Scope of delivery

- ▶ MiniModule AD4 pro MC10 | AD8 pro MC2
- ▶ Configuration software CSMconfig
- ▶ Documentation
- ▶ Calibration certificate in accordance with DIN EN ISO/IEC 17025



Maintenance


- ▶ Calibration every 12 months recommended

Accessories

- ▶ See datasheet "CAN Accessories"

Technical data

Type designation	AD4 pro MC10	AD8 pro MC2
Technical data valid as of revision	H400	J400
		
Inputs	4 voltage inputs	8 voltage inputs
Measurement ranges	± 10 , ± 20 , ± 50 , ± 100 , ± 200 , ± 500 mV and ± 1 , ± 2 , ± 5 , ± 10 , ± 20 , ± 60 V	
Internal resolution	16 bit	
Internal sampling rate per ch.	10 kHz	2 kHz
Measurement data rate/ sending rate per channel	1, 2, 5, 10, 20, 50, 100, 200, 500 Hz and 1 kHz, 2 kHz, 5 kHz ¹ , 10 kHz ¹	1, 2, 5, 10, 20, 50, 100, 200, 500 Hz and 1 kHz, 2 kHz
	adjustable per module or per channel via configurable CAN identifier	
HW input filter	Low-pass filter 3 rd order, approx. 2.5 kHz	Low-pass filter 3 rd order, approx. 500 Hz
SW input filter	switchable 6 th order Butterworth filter, range: 0.1 Hz to 2 kHz automatically adjusted to sending rate, alternatively: cutoff frequency adjustable per channel or switchable average value per sending interval	switchable 6 th order Butterworth filter, range: 0.1 Hz to 500 Hz automatically adjusted to sending rate, alternatively: cutoff frequency adjustable per channel or switchable average value per sending interval or moving average value
Channel-specific comments	free text consisting of up to 100 characters per channel	
Interpolation tables	4 tables, each with up to 32 points	8 tables, each with up to 32 points
Input protection ² Operational safety Device safety	± 60 V permanent ± 100 V permanent, additional ESD protection	
TEDS functionality supported	according to IEEE 1451.4 (template 30 + template 40)	
Gain error ³		
at 25 °C	max. ± 0.05 % of measured value	
Temperature drift	max. ± 10 ppm/K	
Sensor excitation	bipolar, switchable and adjustable per channel ⁴	
Voltage	± 5 , ± 8 , ± 10 , ± 12 , ± 15 V DC	
Current	per channel typ. ± 60 mA, max. ± 120 mA ⁵ , per module max. ± 240 mA	per channel typ. ± 30 mA, max. ± 120 mA ⁵ , per module max. ± 240 mA
Galvanic isolation ⁶	no safety isolation in terms of high-voltage applications	
Channel/channel	500 V	
CAN/channel	500 V	
CAN/power supply	500 V	
CAN interface	CAN 2.0B (active), High Speed (ISO 11898-2:2016), 125 kbit/s to max. 1 Mbit/s, up to 2 Mbit/s with suitable CAN interface, data transfer free running	
Configuration	via CAN bus using CSMconfig or CSM INCA AddOn, settings and configurations stored in the module	

Type designation	AD4 pro MC10	AD8 pro MC2
Power supply		
Minimum ⁴	6 V DC (-10 %)	
Maximum	50 V DC (+10 %)	
Power consumption ⁷	typ. 0.9 W (without sensor excitation)	typ. 1.3 W (without sensor excitation)
LED indicators		
CAN	power/status	
Measurement channels	configuration/operation/sensor excitation	
Housing	aluminum, gold anodized	
Protection class	IP67	
Weight (device)	approx. 300 g	approx. 500 g
Dimensions (w × h × d)	approx. 120 × 32 × 50 mm approx. 120 × 37 × 50 mm (Slide Case)	approx. 200 × 35 × 50 mm approx. 200 × 40 × 50 mm (Slide Case)
Connectors ⁸		
CAN/power supply	LEMO 0B, 5-pole, code G	
Signal inputs	LEMO 0B, 6-pole, code A	
Operating and storage conditions		
Operating temperature range	-40 °C to +125 °C	
Relative humidity	5 % to 95 %	
Pollution degree	3	
Storage temperature	-55 °C to +150 °C	
Conformity		

¹ 5 kHz: 2 channels @ 500 kbit/s CAN bus, 4 channels @ 1 Mbit/s CAN bus, 10 kHz: 2 channels @ 1 Mbit/s CAN bus, 4 channels @ 2 Mbit/s CAN bus.

² Observe information regarding the intended use. See CSM document "Safety Instructions MiniModules".

³ Further information can be found in the Technical Information document on the subject of "Deviation of Measurement".

⁴ In case of full load (7.2 W) a power supply > 8 V is required (> 10 V as of an operating temperature of +85 °C), see Technical information „Sensor Excitation of AD CAN MM Series“.

⁵ Distributive sensor excitation, see Technical information „Sensor Excitation of AD CAN MM Series“.

⁶ These MiniModules are designed for measurements in vehicles with 12 V, 24 V, or 48 V on-board power supply systems. The maximum operating voltage at the measurement inputs is 60 V. Do not connect directly to systems with higher operating voltages, e.g. high-voltage batteries of hybrid or electric vehicles.

⁷ The specified power consumption increases to up to 1.25 W (AD4) depending on TEDS wiring.

⁸ Optionally available in other variants.



CSM GmbH Headquarters (Germany)

Raiffeisenstraße 36 • 70794 Filderstadt

☎ +49 711-77 96 40 ✉ sales@csm.de

CSM Office Southern Europe (France, Italy)

Site d'Archamps

60, rue Douglas Engelbart • Immeuble ABC 1, Entrée A – 1er étage

74160 Archamps, France

☎ +33 450-95 86 44 ✉ info@csm-produits.fr

CSM Products, Inc. USA (USA, Canada, Mexico)

1920 Opdyke Court, Suite 200 • Auburn Hills, MI 48326

☎ +1 248 836-4995 ✉ sales@csmproductsinc.com

CSM (RoW)

Vector Informatik (China, Japan, Korea, India, Great Britain)

ECM AB (Sweden)

DATRON-TECHNOLOGY (Slovakia, Czech Republic)

Our partners guarantee you worldwide availability.

Feel free to contact us.

CSM GmbH Germany is certified.



All trademarks mentioned are property of their respective owners.

Specifications are subject to change without notice.

CANopen® and CiA® are registered community trademarks of CAN in Automation e.V.

EtherCAT® is registered trademark and patented technology, licensed by Beckhoff Automation GmbH, Germany.