



TH evo CAN MM Series



Product description

TH evo measurement modules are equipped with 8 signal inputs for temperature measurements with thermocouples (K type) and TEDS functionality. They are designed for applications used under extreme operating temperatures, like e.g. in engine compartments.

The measurement inputs are equipped with mini thermo single connectors and additional contacts, allowing the use of custom-engineered thermo plugs with integrated TEDS chips. This enables an unambiguous assignment of points of measurement (channel names), saves time during application and configuration and reduces the risk of errors.

Shipping content

- ▶ MiniModule TH evo
- ▶ Configuration software CSMconfig
- ▶ Documentation
- ▶ Calibration certificate in accordance with DIN EN ISO/IEC 17025

Key features



- ▶ *TEDS functionality according to IEEE 1451.4 (Template 36) and channel names supported*
- ▶ *Measurement data rate up to 200 Hz per channel*
- ▶ *Internal cold junction compensation per channel*
- ▶ *Median11 filter for interference pulse suppression*
- ▶ *Very good measurement accuracy under difficult temperature ranges and environmental conditions*
- ▶ *Very low power consumption*


Maintenance

- ▶ Calibration every 12 months recommended

Accessories

- ▶ See "CAN Accessories" datasheet

Technical data

Type designation	TH8 evo
	
Measurement inputs	8 NiCr-Ni
Measurement ranges	-100 °C to +1372 °C
Internal resolution	16 bit
Internal sampling rate per ch.	1 kHz
Measurement data rate per ch.	1, 2, 5, 10, 20, 50, 100, 200 Hz adjustable per module or per channel via configurable CAN identifier
HW input filter	low-pass filter 150 Hz
SW input filter	FIR filter (Finite Impulse Response), averaging automatically adjusted to measurement data rate median11 filter, single or double measurement data rate
Channel-specific comments	free text consisting of up to 100 characters per channel
Input protection ¹⁾	
Operational safety	±60 V permanent
Device safety	±100 V permanent, additional ESD protection
TEDS functionality supported	according to IEEE 1451.4 (Template 36) and channel names
Broken sensor detection	yes
Cold junction compensation	internal reference per channel
Measurement deviation²⁾	
Gain error at 25 °C	max. ±0.05 % of measured value
Offset and scaling error	typ. ±0.1 K max. ±0.3 K ±12 µV
Gain drift	max. ±10 ppm/K
Zero drift	max. ±4 mK/K
Galvanic isolation ³⁾	no safety isolation in terms of high-voltage applications
Channel / channel	500 V
CAN / channel	500 V
CAN / power supply	500 V
CAN interface	CAN 2.0B (active), High Speed (ISO 11898-2:2016) 125 kbit/s to max. 1 Mbit/s, up to 2 Mbit/s with CSMcan interface, data transfer "free running"
Configuration	via CAN bus with CSMconfig or CSM INCA AddOn settings and configurations are stored in the device
Power supply	
Minimum	6 V DC (-10 %)
Maximum	50 V DC (+10 %)
Power consumption	typ. 800 mW

Type designation	TH8 evo
LED indicators	
CAN	Power / status
Housing	aluminium, gold anodized
Protection class	IP65
Weight	approx. 300 g
Dimensions (w × h × d)	approx. 120 × 33 × 50 mm / approx. 120 × 37 × 50 mm (Slide Case)
Connectors	
CAN / power supply	LEMO 0B, 5-pole, code G
Signal inputs	Miniature thermo connectors
Operating and storage conditions	
Operating temperature range	-40 °C to +125 °C
Relative humidity	5 % to 95 %
Pollution degree	3
Storage temperature	-55 °C to +150 °C
Conformity	CE

¹ Observe information regarding the intended use. See CSM document "Safety Instructions MiniModules".

² Further information can be found in the Technical Information document on the subject of "Deviation of Measurement".

³ These MiniModules are designed for measurements in vehicles with 12 V, 24 V, or 48 V on-board power supply systems. The maximum operating voltage at the measurement inputs is 60 V. Not suitable to be directly connected to systems with higher operating voltages, e.g. high-voltage batteries of hybrid or electric vehicles.

additional products

PTMM evo

PTMM evo MiniModules are designed for temperature measurements with PT100 and PT1000 elements and are available in different housings.



HV TH4 evo

These measurement modules are especially designed for safe temperature measurements on high-voltage components and are excellently suited for applications in the field of e-mobility.





CSM GmbH
Computer-Systeme-Messtechnik

Raiffeisenstr. 36, 70794 Filderstadt, Germany

☎ +49 711 - 77 96 40 ✉ info@csm.de

www.csm.de

CSM GmbH Germany is certified.



To product page
at www.csm.de

