

# HV PT8



## Product description

The **HV PT8** measurement module features eight measurement inputs in 4-wire-connection for PT100 and PT1000 sensors, and has been especially designed for precise temperature measurements in high-voltage environments. The 19-inch version has been specifically designed for test bench applications.

The **HV PT8** measurement module is excellently suited for measuring the temperature of individual battery cells and battery packs in high-voltage batteries. Due to the thin-film design of specific foil PT sensors, it is possible to precisely monitor the temperature of battery cells, even under very limited space conditions.

## Shipping content

- ▶ Measurement module HV PT8
- ▶ Configuration software CSMconfig
- ▶ Documentation
- ▶ Calibration certificate in accordance with DIN EN ISO/IEC 17025
- ▶ HV isolation test certificate



## Key features

- ▶ 8 inputs in 4-wire connection for PT100 and PT1000 sensors with reinforced insulation
- ▶ Individual PT coefficients can be entered for best possible sensor adjustment
- ▶ Type approval test and routine test according to safety standard EN 61010


## Maintenance

- ▶ HV isolation test at least every 12 months, see EN 61010 for scope of testing
- ▶ Calibration every 12 months recommended

## Accessories

- ▶ See datasheet "CAN Accessories"

## Technical data

<b>Type designation</b>	<b>HV PT8</b>
	
<b>Measurement inputs</b>	8 inputs in 4-wire connection for PT100 and PT1000 sensors, configurable via software
Measurement ranges	-50 °C to +100 °C and -100 °C to +500 °C
Internal resolution	16 bit
Internal sampling rate per ch.	8 kHz
Measurement data rate/sending rate per channel	1, 2, 5, 10, 20, 50, 100 Hz adjustable per module or per channel via configurable CAN identifier
HW input filter	4th order Butterworth filter (threshold frequency approx. 2.5 kHz <sup>1</sup> )
SW input filter	FIR filter (Finite Impulse Response) threshold frequency automatically adjusted to measurement data rate
Channel-specific comments	free text consisting of up to 100 characters per channel
Linearization	via individual PT coefficients R0, A, B and C
Measurement current	PT100: 500 µA, PT1000: 400 µA
<b>Measurement deviation<sup>2</sup></b>	
Gain error at 25 °C	max. ±0.1 % of measured value
Offset and scaling error	max. ±0.25 K (PT100) / ±0.175 K (PT1000)
Gain drift	max. ±10 ppm/K of measured value
Zero drift	max. ±3 mK/K
<b>Fields of application<sup>3</sup></b>	for measurements in HV environments <sup>4</sup>
Working voltages <sup>4</sup>	up to 846 V DC
<b>Isolation test<sup>3</sup></b>	
Type approval test	by external accredited test laboratory <sup>4</sup>
Routine test	test voltage <sup>4</sup> 3,100 V DC isolation test is to be performed at least every 12 months
<b>Reinforced insulation<sup>3,4</sup></b>	
Channel/channel	846 V
Channel/CAN	846 V
Channel/power supply	846 V
<b>Functional insulation</b>	
CAN/power supply	designed for supply voltages 12V and 24V
<b>CAN interface</b>	CAN 2.0B (active), High Speed (ISO 11898-2:2016) 125 kbit/s to 1 Mbit/s, up to 2 Mbit/s with suitable CAN interface, data transfer rate free running
Configuration	via CAN bus with CSMconfig or CSM INCA AddOn, settings and configurations stored in the device

<b>Type designation</b>	<b>HV PT8</b>
<b>Power supply</b>	
Minimum	6 V DC (-10 %)
Maximum	30 V DC (+10 %)
Power consumption	typ. 3 W
<b>LED indicator</b>	
CAN	power/status
Measurement channels	configuration/operation
<b>Housing</b>	aluminum with HV designation on the front-side (RAL 2003)
Protection class	IP65
Ground connection	M6 threaded hole
Mounting	19 inch
Weight	approx. 735 g
Dimensions (w × h × d)	19 HP (approx. 96 mm) 3 U (approx. 129 mm) 100 mm (+ 25 mm protective bracket)
<b>Connectors</b>	
CAN/power supply <sup>5</sup>	LEMO 0B, 5-pole, code G
Signal inputs	LEMO Redel 2P, 8-pole, code C (grey)
<b>Operating and storage conditions</b>	
Operating temperature range	-40 °C to +85 °C
Relative humidity	5 % to 95 % (non-condensing)
Operating altitude	max. 5,000 m above sea level
Pollution degree	3
Storage temperature	-40 °C to +85 °C
<b>Conformity<sup>6</sup></b>	<b>CE</b>
<b>Device safety</b>	EN 61010-1:2020+COR1:2022 EN 61010-2-030:2022

<sup>1</sup> As of hardware revision A003. For older hardware revisions, a frequency of 5 kHz applies.

<sup>2</sup> In interference-polluted environments, additional measurement errors can occur.  
Further information can be found in the Technical Information document on the subject of "Deviation of Measurement".

<sup>3</sup> Please read the CSM document "Safety Instructions HV PT-TBM".

<sup>4</sup> According to EN 61010-1:2020+COR1:2022 with EN 61010-2-030:2022

<sup>5</sup> Optionally available in other variants

<sup>6</sup> The measurement modules are designed for cable lengths < 3 m.



**CSM GmbH Headquarters** (Germany)

Raiffeisenstraße 36 • 70794 Filderstadt  
☎ +49 711-77 96 40 ✉ sales@csm.de

**CSM Office Southern Europe** (France, Italy)

Site d'Archamps  
178, rue des Frères Lumière • Immeuble Alliance – Entrée A  
74160 Archamps France  
☎ +33 450-95 86 44 ✉ info@csm-produits.fr

**CSM Products, Inc. USA** (USA, Canada, Mexico)

1920 Opdyke Court, Suite 200 • Auburn Hills, MI 48326  
☎ +1 248 836-4995 ✉ sales@csmproductsinc.com

**CSM** (RoW)

**Vector Informatik** (China, Japan, Korea, India, Great Britain)

ECM AB (Sweden)

DATRON-TECHNOLOGY (Slovakia, Czech Republic)

Our partners guarantee you worldwide availability.  
Feel free to contact us.

CSM GmbH Germany is certified.



All trademarks mentioned are property of their respective owners.  
Specifications are subject to change without notice.  
CANopen® and CiA® are registered community trademarks of CAN in Automation e.V.  
EtherCAT® is registered trademark and patented technology, licensed by Beckhoff Automation GmbH, Germany.