



# STG6 CAN MM Series

## Type BK10



### Distributed strain gauge measurement

**STG6 BK10** is a robust and extremely compact CAN-based measurement module for strain gauge measurements and is excellently suited for distributed measurement applications. This provides opportunities to reduce the cabling efforts, to save space and to speed up the setup of measurement applications.

Ratiometric measuring principle and configurable software filter ensure a high resistance to interference. Furthermore, the **STG6 BK10** measurement module features an extremely low power consumption.

### Shipping content

- ▶ Measurement module STG6 BK10
- ▶ Configuration software CSMconfig
- ▶ Documentation
- ▶ Calibration certificate

### Key features



- ▶ *Support of full and half bridge strain gauges with 6- and 4-wire connection*
- ▶ *Support of quarter bridges via special cable K356*
- ▶ *Simple configuration via CSMconfig using a universal measurement range*
- ▶ *Very good measurement accuracy under challenging temperature ranges and environmental conditions*
- ▶ *High resistance to interference due to ratiometric measuring principle and configurable software filter*


### Maintenance


- ▶ Calibration every 12 months recommended

### Accessories

- ▶ See datasheet "CAN Accessories"

## Technical data

<b>Type designation</b>	<b>STG6 BK10</b>
	
<b>Measurement inputs</b>	6 strain gauge inputs
Type of bridge	full and half bridges 120, 350, 700, 1000 Ω, quarter bridges 120 Ω and 350 Ω via special cable K356 with preconfigured TEDS
Bridge connection	4- and 6-wire
Measuring unit	mV/V, μm/m
Input voltage range	±200 mV
Internal resolution	eff. 21 bit
Bridge balancing	via configuration software, up to 50 % of input voltage range
Time synchronization	better than 1 μs
Measurement data rate / sending rate per ch.	1, 2, 5, 10, 20, 50, 100, 200, 500 Hz and 1, 2, 5 <sup>1)</sup> , 10 <sup>1)</sup> kHz
HW input filter	low-pass filter, 3rd order, approx. 2.5 kHz
SW input filter	low pass, 6th order Butterworth filter, range: 0.1 Hz to 2 kHz, switchable
Input protection <sup>2)</sup>	±20 V permanent, additional ESD protection
<b>Measurement deviation</b>	
Gain error <sup>3)</sup> at 25 °C	max. ±0.05 % of measured value
Offset and scaling error	depending on the measurement range
40 mV - 200 mV	max. ±0.01 %
20 mV - 40 mV	max. ±0.02 %
6 mV - 20 mV	max. ±0.05 %
3 mV - 6 mV	max. ±0.1 %
Gain drift <sup>3)</sup>	±10 ppm/K
Zero drift	0.5 μV/K
<b>Noise</b>	at 5 V excitation voltage (peak-to-peak)
$f_g \leq 10$ Hz	< 1 μV/V
10 Hz < $f_g \leq 100$ Hz	< 2 μV/V
100 Hz < $f_g \leq 1$ kHz	< 6 μV/V
<b>Excitation voltage</b>	from 1 to 5 V in 0.5 V steps (adjustable per channel, optionally switchable) max. 42 mA per channel
<b>CAN interface</b>	CAN 2.0B (active), High Speed (ISO 11898-2:2016), 125 kbit/s to 1 Mbit/s, up to 2 Mbit/s with CSMcan interface, data transfer rate is free running
Configuration	via CAN bus with CSMconfig or CSM INCA AddOn settings and configurations stored in the device

<b>Type designation</b>	<b>STG6 BK10</b>
<b>Galvanic isolation</b> <sup>2) 4)</sup>	no safety isolation in terms of high-voltage applications
Channel / channel	500 V
Channel / CAN	500 V
Channel / power supply	500 V
Power supply / bridge excitation voltage	500 V
<b>Power supply</b>	
Minimum	6 V DC (-10 %)
Maximum <sup>5)</sup>	50 V DC (+10 %)
Power consumption <sup>6)</sup>	typ. 1.5 W (without sensor excitation), typ. 2 W (all channels with 350 Ω full bridges and 5 V bridge excitation voltage)
<b>LED indicators</b>	
CAN	power / status
Measurement channels	configuration / operation
<b>Housing</b>	
Protection class	IP67
Weight	approx. 790 g
Dimensions (w × h × d)	approx. 200 × 35 × 50 mm / approx. 200 × 40 × 50 mm (Slide Case)
<b>Connectors</b>	
CAN / power supply	LEMO 0B, 5-pole, code G
Signal inputs	LEMO 1B, 8-pole, code G
<b>Operating and storage conditions</b>	
Operating temperature range	-40 °C to +85 °C
Relative humidity	5 % to 95 % (non-condensing)
Pollution degree	3
Storage temperature	-55 °C to +90 °C
<b>Conformity</b>	
	
<b>Part numbers</b>	
Standard	ART1013201
Slide Case	ART1013200

<sup>1</sup> 5 kHz: 3 channels @ 1 Mbit/s, 6 channels @ 2 Mbit/s. 10 kHz: 2 channels @ 1 Mbit/s, 3 channels @ 2 Mbit/s.

<sup>2</sup> Observe information regarding the intended use. See CSM document "Safety Instructions MiniModule".

<sup>3</sup> Referring to the units mV/V or μm/m measured by the module

<sup>4</sup> These MiniModules are designed for measurements in vehicles with 12 V or 24 V on-board power supply systems. Not suitable to be directly connected to systems with higher operating voltages, e.g. high-voltage batteries of hybrid or electric vehicles.

<sup>5</sup> Max. power supply 50 V DC (+10 %) as of hardware revision AO11. Hardware revision < AO11: 36 V DC (+10%)

<sup>6</sup> Typ. 3.5 W at max. load (all channels with 120 Ω full bridge strain gauges and 5 V bridge excitation voltage)



## **CSM Products, Inc.**

1920 Opdyke Court, Suite 200 • Auburn Hills, MI 48326 • USA  
Phone: +1 (248) 836-4995 • Fax: +1 (248) 836-4997  
info@csmproductsinc.com • www.csmproductsinc.com

CSM GmbH Germany is certified.



To product page  
at [www.csm.de](http://www.csm.de)

